

# ULTRA

Ultra Energy  
[www.ultraelectronicsenergy.com](http://www.ultraelectronicsenergy.com)

Phone: (512) 434-2800  
Email: [CustomerCare@ultra-nspi.com](mailto:CustomerCare@ultra-nspi.com)

## Product Data Sheet MXB-SM40



The base unit (or brain) connects to the fiber optic cable and provides visual indication of fiber link status. Information is received from up to four input modules that can be cascaded. Each module has a partner module installed on the corresponding base unit. An integrated backplane allows for communications between modules with no external inter-modular connection.

## Features

- MX Multiplexer Base Unit supports up to 16 channels
- I/O Modules are available in 2 and 4 channel versions
- Maximum number of I/O modules per optical side - 4
- Maximum number of I/O devices per optical side - 16
- SFP Transceivers with LC connectors and patch cords available

## Specifications

NAME	DESCRIPTION
Input Power Requirement	+15-30Vdc Input
Alarm Output Relay	Form-C (SPST), 1A @ 30Vdc
Update Rate	115.2kHz (8.68μs)
Connector Type	LC
Compatible Fiber Type	Single Mode
Maximum Transmission Distance	40km
Regulatory Certifications	CE, Class I, Division 2, Groups A, B, C & D for the US & Canada, ATEX, Zone-2, Category 3
Operating Temperature	-40 to 85°C; 0-95% Humidity (non-condensing)
Mounting	35mm DIN Rail
Weight	<9oz. (250g)
Legacy Modules	2M61

## Accessories

---

**Contact Closure I/O Modules**

MXCC-IP2, MXCC-IP4, MXCC-OP2, MXCC-OP4

---

**4-20mA I/O Modules**

MX420-IP2, MX420-IP4, MX420-OP2, MX420-OP4

---

**0-10Vdc I/O Modules**

MX010-IP2, MX010-IP4, MX010-OP2, MX010-OP4

---

**RS232/485**

MXRS-2, MXRS-4

## Documents

---

**NAME**

**VIEW / DOWNLOAD**

---

**Installation Instructions**

[View / Download](#)